

## INSTRUCTIONS FOR THE ASSEMBLING OF THE SELO LIGHTING SET.

The Selo Lighting Set comprises folding reflector, reflector- holder and stand, flex, lamp-holder and plug adapter, two octagonal caps and one Photoflood lamp.

To assemble the set the reflector is opened and held in this position by means of the two octagonal caps, the larger cap marked '0' being on the outside. The shade ring is removed from the lamp-holder and the holder is passed first through the circular opening in the reflector-holder and then through the reflector from the back. The shade ring is then screwed tightly into place on the lamp-holder to keep everything rigid and in position. The reflector-holder is adjustable and is provided with a thumb screw so it may be locked in any position-it may be necessary to ease this screw and to raise the reflector-holder somewhat to allow the lamp-holder to pass through the reflector as described above. The position of the stand with regard to the base can also be adjusted and the adjustment maintained by means of the clamp. These two adjustments make the Selo Lighting Set adaptable for use in an almost unlimited number of positions and in addition it may be hung in position by means of the metal loop.

Note: When dismantling the Lighting Set the reflector should first be allowed to fall flat. It should then be grasped by the opposite corners and the hands pushed together so that the reflector is made to form a four-pointed star which is then allowed to collapse upon itself. The reflector is thus folded upon a base consisting of two sections. No attempt must be made made to fold it into a smaller compass.

ILFORD LIMITED, ILFORD, LONDON.

M.37